

LTC3576EUFE-1

 Switching Power Manager + USB On-the-Go
+ OVP + HV Buck VC Control + 3 Bucks

DESCRIPTION

Demonstration Circuit DC1577A is a Switching Power Manager with USB On-the-Go + Triple Step Down DC/DCs. The LTC3576EUFE-1 is available in a 38-pin (4mm × 6mm) QFN surface mount package.

LTC, LTC, LTM, LT, Burst Mode, OPTI-LOOP, Over-The-Top and PolyPhase are registered trademarks of Linear Technology Corporation. Adaptive Power, C-Load, DirectSense, Easy Drive, FilterCAD, Hot Swap, LinearView, µModule, Micropower SwitcherCAD, Multimode Dimming, No Latency $\Delta\Sigma$, No Latency Delta-Sigma, No R_{SENSE} , Operational Filter, PanelProtect, PowerPath, PowerSOT, SmartStart, SoftSpan, Stage Shredding, SwitcherCAD, ThinSOT, UltraFast and VLDO are trademarks of Linear Technology Corporation. Other product names may be trademarks of the companies that manufacture the products.

PERFORMANCE SUMMARY Specifications are at $T_A = 25^\circ\text{C}$

SYMBOL	PARAMETER	CONDITIONS	MIN	TYP	MAX	UNITS
V _{USB}	V _{USB} Input Voltage Range	Input disabled from 6V–30V	4.35	30		V
V _{OUT}	V _{OUT} Output Voltage Range	Range is mode and load dependant	3.5	5.5		V
V _{BAT}	Output Float Voltage	Constant voltage mode		4.1		V
I _{BAT}	Output Charge Current	Constant current mode		0.5	1	A

SOFTWARE GUI

The DC1577A Demo Circuit can be controlled from a software GUI. Most of the features of the LTC3576EUFE-1 are only accessible via the I²C channel. When the QuikEval program is active and a DC590 with a DC1577A connected and attached to the USB cable, the “LTC3576” form should automatically pop up and be fully operational:




Figure 1. GUI control panel

SOFTWARE OPERATION

The software GUI automatically opens the control panel shown above. This control panel allows control of most major functions of the LTC3576EUFE-1. The EN1, EN2, EN3, and ENOTG signals are wire OR'ed with individual regulator enable regulator signals from the I²C channel. Consequent to this, if the ENx or ENOTG signals are high, the regulators will be enabled regardless of the state of the I²C channel regulator control bits.

Register A, B, C and D display

These are not writeable and are provided as a programming aid. The current value of the I²C A, B, C and D registers are displayed.

Update button

Forces an immediate update of the I²C registers.

Autoupdate button

LTC3576EUFE-1

If enabled (default) will update the I2C channel whenever something is changed.

Battery charger button

If on (default) the battery charger in the LTC3576EUFE-1 will be enabled, and if off the battery charger will be disabled.

VOUT1~VOUT3 buttons

Individually enable or disable the three voltage regulators. These only function if the ENx pins are held low.

Switchmode Regulators mode

Set the mode of operation of all the switchmode regulators.

VOUT1, VOUT2 and VOUT3 sliders

Allow control of voltage regulator 1, 2 and 3 output voltages by adjusting the respective reference DACs.

VOUT1~3 output and reference voltages

These are not writeable, but reflect the current state of the reference DACs, and feedback resistors.

Input current limit

Set the maximum power drawn from the USB port.

Change feedback divider resistor values

This opens the form:




Figure 2. Feedback resistor control panel

This form allows the feedback resistor divider network on each regulator to be changed. The information changed here, is saved, and is durable from session to session. However, the factory values can be recovered by pressing the “Restore defaults” button

QUICK START PROCEDURE

Using short twisted pair leads for any power connections, with all loads and power supplies off, refer to Figures 2 & 3 for the proper measurement and equipment setup.


A companion HV Buck demo board is required for this check out procedure. The DC1394 (LT3480) board is recommended, and will be used for the following procedure. Please refer to the DC1394 Quick Start Guide for further information.

Follow the procedure below:

1. Set “DVCC” jumper (JP9) to “MODE”, JP7 & JP8 to “0”. Do not start the GUI, at this time, as JP9 has disabled the I²C interface.
2. Set PS1 to 5V, and PS4 to 3.6V. Observe that $3.55V < VOUT (VM6) < 3.70V$ and $80mA < I(VUSB) (AM1) < 95mA$. The USB current limit is set for 1X (100mA), and the battery charger is set to 500mA. So, VOUT collapses until the charge current matches the current available from the USB input.
3. Set ILIM1 (JP2) and ILIM0 (JP1) to “1”. Observe that $3.80 < VOUT (VM4) < 4.10V$ and $380mA < I(VUSB) < 420mA$ (AM1). The USB input current limit is now 5X (500mA), and the VOUT switching regulator behaves like a transformer, exchanging output current for output voltage. So, the input current is $\approx (VOUT/VUSB) * 500mA$. Set Load 1 to 0A.
4. Set ILIM1 (JP2) to “0” and ILIM0 (JP1) to “1”. Set Load 1 to 500mA. Observe $4.00V < VOUT < 4.15V$ (VM4) and $760mA < I(VUSB) < 840mA$ (AM1). The USB input current limit is now 10X (1A).
5. Set “DVCC” Jumper (JP9) to “DVCC”, JP7 and JP8 to “DC590”. Start the GUI
6. Set PS1 to 5V, and PS4 to 3.6V. . Observe that $3.55V < VOUT (VM6) < 3.70V$ and $80mA < I(VUSB) (AM1) < 95mA$. The USB current limit is set for 1X (100mA), and the battery charger is set to 500mA. So, VOUT collapses until the charge current matches the current available from the USB input.
7. Use GUI to set “Average input current limit setting” to “5X Mode (500mA). . Observe that $3.55V < VOUT (VM6) < 3.70V$ and $80mA < I(VUSB) (AM1) < 95mA$. The USB current limit is set for 1X (100mA), and the battery charger is set to 500mA. So, VOUT collapses until the charge current matches the current available from the USB input.
8. Use GUI to set “Average input current limit setting” to “10X Mode (1A). Set Load 1 to 500mA. Observe $4.00V < VOUT < 4.15V$ (VM4) and $760mA < I(VUSB) < 840mA$ (AM1). The USB input current limit is now 10X (1A).
9. Set PS1 to 0V, and Load 1 to 0A. Observe that $3.50V < VOUT 3.65V$ (VM6) and $V(VOUT, BAT) < 30mV$ (VM6 - VM7). The ideal diode is now on, with a minimal load on VOUT.
10. Set Load 1 to 1A. Observe that $3.50V < VOUT (VM6) < 3.60V$ and $V(VOUT,BAT) < 0.10V$ (VM6 – VM7). Set Load 1 to 0A. The ideal diode is on and supplying the 1A Load 1 load from the battery.
11. Set NTC (JP4) to “EXT”. Does the “Battery Charging” LED blink? Set NTC (JP4) to “INT”.
12. Set WALL (DC1394, JP3) to “HVBUCK”, COMP (DC1394, JP2) to “REMOTE”, and SYNC (DC1394, JP1) to “RUN/SYNC”. Increase PS2 from 0V to 8V. Observe that $3.80 V < VOUT < 4.10V$ (VM6) and $0.98V < V(PROG) < 1.02V$ (VM5). The HV Buck regulator is now providing power to VOUT, and the internal regulator has stopped supplying power from the USB port.
13. Set Load 1 to 1A. Observe that $3.80V < VOUT < 4.10V$ (VM6) and $0.98V < V(PROG) < 1.02V$ (VM5).

LTC3576EUF-1

14. Set PS2 to 38V. Measure VOUT (VM6) and V (PROG) (VM5). Observe that $3.80V < VOUT < 4.10V$ (VM6) and $0.98V < V (PROG) < 1.02V$ (VM5).
15. Set WALL (DC1394, JP3) to “5V ADAPTOR” and PS3 to 5V. Observe that $4.40V < VOUT < 5.40V$ (VM6) and $0.98V < V (PROG) < 1.02V$ (VM5).
The 5V adaptor is now providing the power VOUT. The voltage of PS3 will not track V (BAT) and the dissipation in the charger will increase.
16. Set Load 1 to 1A. Observe that $4.40V < VOUT < 5.40V$ (VM6) and $0.98V < V (PROG) < 1.02V$ (VM5). Set Load 1 to 0A and set Wall (DC1394, JP3) to “HVBUCK”.
17. Use GUI to enable VOUT1, VOUT2, and VOUT3. Observe that $3.48V < VOUT1 < 3.70V$ (VM10), $3.28V < VOUT2 < 3.49V$ (VM8), and $1.74V < VOUT3 < 1.84V$ (VM9).
18. Set Load 2 to 400mA, Load 3 to 1A, and Load 4 to 400mA. Observe that $3.48V < VOUT1 < 3.70V$ (VM10), $3.28V < VOUT2 < 3.49V$ (VM8), and $1.74V < VOUT3 < 1.84V$ (VM9).
19. Use GUI to set VOUT1, VOUT2, and VOUT3 to minimum. Observe that $1.85V < VOUT1 < 1.96V$ (VM10), $1.74V < VOUT2 < 1.85V$ (VM8), and $0.93V < VOUT3 < 0.977V$ (VM9).
20. Set Load 2 to 0mA, Load 3 to 0mA, and Load 4 to 400mA. Observe that $1.85V < VOUT1 < 1.96V$ (VM10), $1.74V < VOUT2 < 1.85V$ (VM8), and $0.93V < VOUT3 < 0.977V$ (VM9).
21. Use the GUI to disable VOUT1, VOUT2, and VOUT3. Observe that $VOUT1 < 0.1V$ (VM10), $VOUT2 < 0.1V$ (VM8), and $< VOUT3 < 0.1V$ (VM9).



Note: All connections from equipment should be Kelvin connected directly to the Board PINS which they are connected to on this diagram and any input, or output, leads should be twisted pair

Figure 3. Proper Measurement Equipment Setup for DC1577A




Figure 4. Measuring Input or Output Ripple

LTC3576EUFE-1




Figure 5. DC1577A Schematic

Qty	Reference	Part Description	Manufacture / Part #	
REQUIRED CIRCUIT COMPONENTS:				
1	C2, C7,C16	CAP, CHIP, X5R, 22µF, ±20%, 6.3V, 0805	TAIYO-YUDEN, JMK212BJ226MG	
2	C5	CAP, CHIP, X7R, 0.1µF, ±10%, 16V, 0402	MURATA, GRM155R71C104KA88	
3	C6	CAP, CHIP, COG, 27pF, 5%, 50V, 0402	VISHAY, VJ0402A270JXAA	
4	C8,C11,C14	CAP, CHIP, X5R, 2.2µF, 20%, 6.3V, 0402	MURATA, GRM155R60J225ME15D	
5	C9	CAP, CHIP, COG, 18pF, 5%, 50V, 0402	VISHAY, VJ0402A180JXAA	
6	C10,C13	CAP, CHIP, X5R, 10µF, 10%, 6.3V, 0603	TDK, C1608X5R0J106K	
7	C12	CAP, CHIP, COG, 12pF, 50V, 5%, 0402	VISHAY, VJ0402A120JXAA	
8	C17	CAP, CHIP, X5R, 1.0µF, 10%, 10V, 0402	TDK, C1005X5R1A105K	
9	L1	IND, SMT, 2.0µH, ±20%, 1.9A, 3.0mmX3.2mm	TOKO, 1098AS-2R0M	
10	L2,L3	IND, SMT, 4.7µH, ±20%, 1.3A, 3.0mmX3.2mm	TOKO, 1098AS-4R7M	
11	L4	IND, SMT, 3.3µH, ±20%, 2.2A, 4.0mmX4.0mm	COILCRAFT, LPS4018-3R3MLC	
12	Q1	MOSFET, 30V, 65mΩ, 3.5A, SOT-23	VISHAY, Si2306BDS	
13	R2	RES, CHIP, 6.2kΩ, 1/10W, 5%, 0603	VISHAY, CRCW06036K20JNED	
14	R7	RES, CHIP, 3.01kΩ, 1/16W, 1%, 0402	VISHAY, CRCW04023K01FKED	
15	R8	RES, CHIP, 2.00kΩ, 1/16W, 1%, 0402	VISHAY, CRCW04022K00FKED	
16	R13,R17,R20	RES, CHIP, 324kΩ, 1/16W, 1%, 0402	VISHAY, CRCW0402324KFKED	
17	R14	RES, CHIP, 402kΩ, 1/16W, 1%, 0402	VISHAY, CRCW0402402KFKED	
18	R18	RES, CHIP, 1.05MEGΩ, 1/16W, 1%, 0402	VISHAY, CRCW04021M05FKED	
19	R21	RES, CHIP, 1.13MEGΩ, 1/16W, 1%, 0402	VISHAY, CRCW04021M13FKED	
20	U1	Switching Power Manager with USB On-the-Go + Triple Step-Down DC/DCs	LINEAR TECH., LTC3576EUFE-1	
ADDITIONAL DEMO BOARD CIRCUIT COMPONENTS:				
1	C1	CAP, CHIP, X7R, 4.7µF, ±10%, 50V, 1206	MURATA, GRM31CR71H475KA12L	
2	C3,C4	CAP, CHIP, X7R, 0.1µF, ±10%, 16V, 0402	MURATA, GRM155R71C104KA88	
3	C15	CAP, CHIP, X5R, 100µF, ±20%, 6.3V, 1206	MURATA, GRM31CR60J107ME39L	
4	D1	LED, SMT, GREEN, 1206	PANASONIC, LN1351CTR	
5	Q2	MOSFET, -12V, 35mΩ, -5.3A, SOT-23	VISHAY, Si2333DS	
6	R1,R23,R24,R25	RES, CHIP, 1.0Ω, 1/16W, 5%, 0402	VISHAY, CRCW04021R00JNED	
7	R3,R4,R6	RES, CHIP, 5.1kΩ, 5%, 1/16W, 0402	VISHAY, CRCW04025K10JNED	
8	R5,R11,R12	RES, CHIP, 0Ω, 1/16W, 0402	VISHAY, CRCW04020000Z0ED	
9	R9,R10,R16	RES, CHIP, 100kΩ, 1/16W, 1%, 0402	VISHAY, CRCW0402100KFKED	
10	R15,R19,R22	RES, CHIP, 20Ω, 1/16W, 5%, 0402	VISHAY, CRCW040220R0JNED	
11	R26	RES, CHIP, 1.0kΩ, 5%, 1/10W, 0603	VISHAY, CRCW06031K00JNED	
12	U2	I2C EEPROM	MICROCHIP, 24LC025-I/ST	
HARDWARE FOR DEMO BOARD ONLY:				
1	14	E1,E2,E3,E4,E9,E10,E11,E12 E13,E14,E15,E16,E18,E19	Turret, 0.09"	MILL-MAX, 2501-2
2	7	E5,E6,E7,E8,E17,E20,E21	Turret, 0.061"	MILL-MAX, 2308-2
3	1	J1	CONN, USB MICRO-A/B	HIROSE, ZX62-AB-5PA
4	1	J2	CONN, USB MINI-A/B	MOLEX, 56579-0576
5	1	J3	CONN, I2C header	MOLEX, 87831-1420
6	0	J4-OPT	CONN, Battery	HIROSE, DF3-3P-2DSA
	1	J5	CONN, HV interface	SAMTEC, SQT-108-01-F-D-RA
7	10	JP1,JP2,JP3,JP4,JP5, JP6,JP7,JP8,JP9,JP10	3 Pin Jumper, 2mm	SAMTEC, TMM-103-02-L-S
8	10	JP1,JP2,JP3,JP4,JP5, JP6,JP7,JP8,JP9,JP10	2mm SHUNT	SAMTEC, 2SN-BK-G
9	2	JP11,JP12	2 Pin Jumper, 2mm	SAMTEC, TMM-102-02-L-S
10	4		STAND-OFF, NYLON 0.375" tall (SNAP ON)	KEYSTONE, 8832 (SNAP ON)

Figure 6. DC1577A BOM



Компания «ЭлектроПласт» предлагает заключение долгосрочных отношений при поставках импортных электронных компонентов на взаимовыгодных условиях!

Наши преимущества:

- Оперативные поставки широкого спектра электронных компонентов отечественного и импортного производства напрямую от производителей и с крупнейших мировых складов;
- Поставка более 17-ти миллионов наименований электронных компонентов;
- Поставка сложных, дефицитных, либо снятых с производства позиций;
- Оперативные сроки поставки под заказ (от 5 рабочих дней);
- Экспресс доставка в любую точку России;
- Техническая поддержка проекта, помошь в подборе аналогов, поставка прототипов;
- Система менеджмента качества сертифицирована по Международному стандарту ISO 9001;
- Лицензия ФСБ на осуществление работ с использованием сведений, составляющих государственную тайну;
- Поставка специализированных компонентов (Xilinx, Altera, Analog Devices, Intersil, Interpoint, Microsemi, Aeroflex, Peregrine, Syfer, Eurofarad, Texas Instrument, Miteq, Cobham, E2V, MA-COM, Hittite, Mini-Circuits, General Dynamics и др.);

Помимо этого, одним из направлений компании «ЭлектроПласт» является направление «Источники питания». Мы предлагаем Вам помошь Конструкторского отдела:

- Подбор оптимального решения, техническое обоснование при выборе компонента;
- Подбор аналогов;
- Консультации по применению компонента;
- Поставка образцов и прототипов;
- Техническая поддержка проекта;
- Защита от снятия компонента с производства.



Как с нами связаться

Телефон: 8 (812) 309 58 32 (многоканальный)

Факс: 8 (812) 320-02-42

Электронная почта: org@eplast1.ru

Адрес: 198099, г. Санкт-Петербург, ул. Калинина, дом 2, корпус 4, литера А.