

HA12237F

Audio Signal Processor for Cassette Deck

REJ03F0137-0100
(Previous: ADE-207-343)
Rev.1.00
Jun 15, 2005

Description

HA12237F is silicon monolithic bipolar IC providing PB equalizer, REC equalizer system, ALC and each electronic control switch in one chip.

Functions

- PB equalizer × 2 channel
- REC equalizer × 2 channel
- ALC (Automatic Level Control)
- REC mute
- REC head return switch
- Line Amp. × 2 channel
- Line mute

Features







- REC equalizer is very small number of external parts built-in 2 types of frequency characteristics.
- TYPE I REC correspondence, High-speed dubbing correspondence.
- PB equalizer circuit built-in 2 types of frequency characteristics. (external parts of capacitor only)
- Head control switch built-in.
- Line mute switch built-in.
- Controllable from direct micro-computer output.

Parallel Data Format

Pin No.	Pin Name	Lo	Hi
11	ALC ON/ $\overline{\text{OFF}}$	ALC OFF	ALC ON
12	High/ $\overline{\text{Norm}}$	Normal speed	High speed
13	A/ $\overline{\text{B}}$	B	A
	REC Return ON/ $\overline{\text{OFF}}$	Return OFF	Return ON
14	MUTE ON/ $\overline{\text{OFF}}$	MUTE OFF	MUTE ON
15	REC MUTE OFF/ $\overline{\text{ON}}$	REC MUTE ON	REC MUTE OFF





Pin Description, Equivalent Circuit

(V_{CC} = 12 V, T_a = 25°C, No Signal, The value in the table shows typical value.)


Pin No.	Pin Name	Note	Equivalent Circuit	Description	
16	V _{CC}	V = V _{CC}		V _{CC} pin	
21	RECOUT(L)	V = V _{CC} /2		REC output	
10	RECOUT(R)			PB output	
26	PBOUT(L)			EQ output	
5	PBOUT(R)				
28	EQOUT(L)				
3	EQOUT(R)	V = 2.9 V			
35	REC-RETURN	V = 0 V		REC Return	
34	BIN(L)			PB B deck input	
37	BIN(R)				
32	AIN(L)	V = 0 V		PB A deck input	
39	AIN(R)				
24	RECIN(L)	V = V _{CC} /2		REC-EQ input	
7	RECIN(R)	V = V _{CC} /2		Tape input	
27	TAI(L)				
4	TAI(R)				
11	ALC ON/OFF	(Control voltage = 3 V)		Mode control input	
12	High/Norm			Equalizer reference current input	
13	A/B				
14	MUTE ON/OFF				
15	REC MUTE OFF/ON				
19	IREF	V = 1.2 V			

Pin Description, Equivalent Circuit (cont.)

(V_{CC} = 12 V, T_a = 25°C, No Signal, The value in the table shows typical value.)

Pin No.	Pin Name	Note	Equivalent Circuit	Description
18, 36	GND			GND pin
6, 9, 22, 25, 38	NC			NC pin
20	Test mode			Test mode pin
31	PB-NF1(L)	V = 0.6 V		PB EQ feed back
40	PB-NF1(R)			
30	PB-NF2(L)			
1	PB-NF2(R)			
33	RIP	V = V _{CC} /2		Ripple filter
29	PB-EQ(L)			NAB output
2	PB-EQ(R)			

Block Diagram



Functional Description

Power Supply Range

This IC designed to operate on single supply, shown by table 1.

Table 1 Supply Voltage

Item	Power Supply Range
Single supply	6.5 V to 15.0 V

Reference Voltage

This device provide the reference voltage of half the supply voltage that is the signal grounds. As the peculiarity of this device, the capacitor for the ripple filter is very small about 1/100 compared with their usual value. The block diagram is shown as figure 1.




Figure 1 Block Diagram of Reference Supply Voltage

Operating Mode Control

HA12235F provide fully electronic switching circuits. And each operating mode control is controlled by parallel data (DC voltage).

Table 2 Threshold Voltage (V_{TH})

Pin No.	Lo	Mid	Hi	Unit	Test Condition
11 to 15	-0.2 to 0.5	—	2.4 to V_{CC}	V	Input Pin Measure

- Notes: 1. Each pins are on pulled down with 100 k Ω internal resistor. Therefore, it will be low-level when each pins are open.
2. Over shoot level and under shoot level of input signal must be the standardized.
(High: V_{CC} , Low: -0.2 V)

Test Mode

Test mode becomes when pin 20 is shorted to GND. Please open pin 20 on the occasion of mount.

Block Diagram

As this IC is built-in REC return switch, the configuration system can be simple system using a few external component and the REC/PB head.

About these logics, please look at the Parallel Data Format.




Figure 2 Block Diagram (Lch)

PB Equalizer

The gain establishment of PB-EQ considers PB output level {(internal Line Amp. + PB Amp.) = 580 mVrms} like figure 3 at the target.

After replace RA and RB with a half-fix volume, adjust level.

REC-EQ adjust the gain in front of input to this IC.

The level digram of 1 kHz is shown figure 3.

Please set “ $RA + RB \geq 10 \text{ k}\Omega$ ”




Figure 3 PB System Level Diagram (1 kHz)

Line Mute

This IC is built-in with mute circuit to Line Amp.

A mute control does with Low/High of pin 14.

Reducing pop noise is so much better 10 k Ω to 22 k Ω resistor to pin 14 in series and 1 μ F to 22 μ F capacitor.

A mute is not built-in when doing a power ON/OFF.

Please correspond to it, on the side of a set system.

REC Equalizer

REC-EQ gain adjust before the input of this IC.

R_L needs the value more than 5.6 k Ω based on the output at reference input.

Because mode establishment resistances are built-in, REC-EQ frequency characteristics are respectively fixed value.

In case the change of the frequency characteristics are necessary, please inquire the responsible agent because the adjustment of resistors is necessary.




Figure 4 REC-EQ Block Diagram

ALC (Automatic Level Control)

ALC is the input decay rate variable system. It has internal variable resistors of pin 8 (pin 23) by REC signal that is inputted to pin 7 (pin 24).

Pin 17 is detector pin.

The signal input pin is pin 7 (pin 24). Resistor R1, R2 and capacitor C2, external components, for the input circuit are commended as figure 4. There are requested to use value of the block diagram figure for performance maintenance of S/N, T.H.D. etc.

Figure 5 shows the relation with R1 and C1 front input point and RECOUT.

ALC operation level acts for the center of +4.5 dB to standard level (453 mVrms).

Then, adopted maximum value circuit, ALC is operated by a large channel of signal.

ALC ON/OFF can switch it by pin 11. Please do ALC ON, after it does for one time ALC OFF inevitably, for ALC time to start usefully, in order to reset ALC circuit.




Figure 5 ALC Operation Level

Absolute Maximum Ratings

(Ta = 25°C)

Item	Symbol	Rating	Unit	Note
Maximum supply voltage	V _{CC} Max	16	V	
Power dissipation	P _T	625	mW	Ta ≤ 75°C
Operating temperature	T _{opr}	−40 to +75	°C	
Storage temperature	T _{stg}	−55 to +125	°C	
Operating voltage	V _{opr}	6.5 to 15	V	

Note: HA12235F operates on single supply voltage.

Electrical Characteristics

(Ta = 25°C, V_{CC} = 12 V, PB-EQIN Standard level = 0.6 mVrms at 1 kHz, TAI Standard level = 30 mVrms, PBOU Standard level = 580 mVrms)

Item	Symbol	Test Condition				Specification				Application Terminal			
		IC Condition		fin (Hz)	Vin (mVrms)	Other	Min	Typ	Max	Unit	Input		Output
		A/B	High/ Norm								R	L	COM
Quiescent current	I _Q	A	Norm	OFF	—	No signal	—	12.2	20.2	mA	—	—	16
Logical threshold	V _{IL}	—	—	—	—	—	—0.2	—	0.5	V	—	—	11 to 15
	V _{IH}	—	—	—	—	—	2.4	—	V _{CC}	V	—	—	11 to 15
PB-REC crosstalk	GT PB/REC(1)	A	Norm	OFF	1k	REC-EQ→PB-EQ	50.0	60.0	—	dB	7	24	28
	GT PB/REC(2)	A	Norm	OFF	1k	PB-EQ→REC-EQ	60.0	70.0	—	dB	39	32	10
PB-EQ gain	GV PB(1)	A/B	Norm	OFF	1k	—	37.4	40.4	43.4	dB	39/37/28/29	3	28
	GV PB(2)	A	Norm	OFF	10k	—	33.3	36.3	39.3	dB	39	32	28
	GV PB(3)	A	High	OFF	20k	—	31.2	34.2	37.2	dB	39	32	28
	Vomax PB	A	Norm	OFF	1k	THD = 1%	0.3	0.6	—	Vrms	39	32	28
PB-EQ T.H.D.	THD PB	A/B	Norm	OFF	1k	—	—	0.2	0.5	%	39/37/28/29	3	28
PB-EQ noise voltage	VN PB	A/B	Norm	OFF	—	Rg = 680Ω, DIN-AUDIO	—	110	200	μVrms	39/37/28/29	3	28
PB-EQ channel separation	CT R/L(1)	A	Norm	OFF	1k	—	50.0	60.0	—	dB	39	32	28
PB-EQ crosstalk	CT A/B	A/B	Norm	OFF	1k	—	60.0	70.0	—	dB	39/37/28/29	3	28
Line Amp. gain	G _v LA	A	Norm	OFF	1k	—	24.2	25.7	27.2	dB	4	27	5
Line Amp. T.H.D.	THD LA	A	Norm	OFF	1k	—	—	0.05	0.30	%	4	27	5
Line Amp. maximum output level	Vomax LA	A	Norm	OFF	1k	THD = 1%	1.16	1.40	—	Vrms	4	27	5
Line mute attenuation	L-MUTE ATT	A	Norm	OFF	1k	—	70.0	80.0	—	dB	4	27	5

Notes: 1. Large level without clipping

2. V_{CC} = 6.5V

Electrical Characteristics (cont.)


(Ta = 25°C, V_{CC} = 12 V, RECIN Standard level = 200 mVrms (IC in Level = 25.5 mVrms) = 0 dB

Item	Symbol	Test Condition										Application Terminal				COM Remark
		IC Condition		fin (Hz)	Vin (mVrms)	Other	Specification			Input		Output				
		A/B	High/ Norm				Min	Typ	Max	R	L	R	L			
ALC operate level	ALC	A	Norm	ON	1k	+12		2.0	4.5	7.0	dB	7	24	10	21	—
REC-EQ frequency characteristics	GV REC-NN1	A	Norm	OFF	1k	−26		23.5	25.0	26.5	dB	7	24	10	21	—
Normal speed	GV REC-NN2	A	Norm	OFF	5k	−26		26.9	28.9	30.9	dB	7	24	10	21	—
	GV REC-NN3	A	Norm	OFF	10k	−26		33.2	35.7	38.2	dB	7	24	10	21	—
	GV REC-HN1	A	High	OFF	2k	−26		23.4	24.9	26.4	dB	7	24	10	21	—
High speed	GV REC-HN2	A	High	OFF	10k	−26		26.5	28.5	30.5	dB	7	24	10	21	—
	GV REC-HN3	A	High	OFF	20k	−26		33.4	35.9	38.4	dB	7	24	10	21	—
	CT R/L(2)	A	Norm	OFF	1k	*1		61.0	70.0	—	dB	7	24	10	21	—
REC-MUTE attenuation	R-MUTE ATT	A	Norm	OFF	1k	*1		66.0	76.0	—	dB	7	24	10	21	—
REC-EQ maximum output level	Vomax REC	A	Norm	OFF	1k	—	THD = 1%	0.7	1.0	—	Vrms	7	24	10	21	*2
REC-EQ T.H.D.	THD REC	A	Norm	OFF	1k	0		—	0.2	0.5	%	7	24	10	21	—
REC-EQ S/N	S/N REC	A	Norm	OFF	1k	—	Rg = 2.2kΩ, A-WTG	55.0	59.0	—	dB	—	—	10	21	—



Notes: 1. Large level without clipping



2. V_{CC} = 6.5V



Test Circuit







Characteristic Curves




































































Package Dimensions



Renesas Technology Corp. Sales Strategic Planning Div. Nippon Bldg., 2-6-2, Ohte-machi, Chiyoda-ku, Tokyo 100-0004, Japan

Keep safety first in your circuit designs!

1. Renesas Technology Corp. puts the maximum effort into making semiconductor products better and more reliable, but there is always the possibility that trouble may occur with them. Trouble with semiconductors may lead to personal injury, fire or property damage.
Remember to give due consideration to safety when making your circuit designs, with appropriate measures such as (i) placement of substitutive, auxiliary circuits, (ii) use of nonflammable material or (iii) prevention against any malfunction or mishap.

Notes regarding these materials

1. These materials are intended as a reference to assist our customers in the selection of the Renesas Technology Corp. product best suited to the customer's application; they do not convey any license under any intellectual property rights, or any other rights, belonging to Renesas Technology Corp. or a third party.
2. Renesas Technology Corp. assumes no responsibility for any damage, or infringement of any third-party's rights, originating in the use of any product data, diagrams, charts, programs, algorithms, or circuit application examples contained in these materials.
3. All information contained in these materials, including product data, diagrams, charts, programs and algorithms represents information on products at the time of publication of these materials, and are subject to change by Renesas Technology Corp. without notice due to product improvements or other reasons. It is therefore recommended that customers contact Renesas Technology Corp. or an authorized Renesas Technology Corp. product distributor for the latest product information before purchasing a product listed herein.
The information described here may contain technical inaccuracies or typographical errors.
Renesas Technology Corp. assumes no responsibility for any damage, liability, or other loss rising from these inaccuracies or errors.
Please also pay attention to information published by Renesas Technology Corp. by various means, including the Renesas Technology Corp. Semiconductor home page (<http://www.renesas.com>).
4. When using any or all of the information contained in these materials, including product data, diagrams, charts, programs, and algorithms, please be sure to evaluate all information as a total system before making a final decision on the applicability of the information and products. Renesas Technology Corp. assumes no responsibility for any damage, liability or other loss resulting from the information contained herein.
5. Renesas Technology Corp. semiconductors are not designed or manufactured for use in a device or system that is used under circumstances in which human life is potentially at stake. Please contact Renesas Technology Corp. or an authorized Renesas Technology Corp. product distributor when considering the use of a product contained herein for any specific purposes, such as apparatus or systems for transportation, vehicular, medical, aerospace, nuclear, or undersea repeater use.
6. The prior written approval of Renesas Technology Corp. is necessary to reprint or reproduce in whole or in part these materials.
7. If these products or technologies are subject to the Japanese export control restrictions, they must be exported under a license from the Japanese government and cannot be imported into a country other than the approved destination.
Any diversion or reexport contrary to the export control laws and regulations of Japan and/or the country of destination is prohibited.
8. Please contact Renesas Technology Corp. for further details on these materials or the products contained therein.



RENESAS SALES OFFICES

<http://www.renesas.com>

Refer to "<http://www.renesas.com/en/network>" for the latest and detailed information.

Renesas Technology America, Inc.

450 Holger Way, San Jose, CA 95134-1368, U.S.A
Tel: <1> (408) 382-7500, Fax: <1> (408) 382-7501

Renesas Technology Europe Limited

Dukes Meadow, Millboard Road, Bourne End, Buckinghamshire, SL8 5FH, U.K.
Tel: <44> (1628) 585-100, Fax: <44> (1628) 585-900

Renesas Technology Hong Kong Ltd.

7th Floor, North Tower, World Finance Centre, Harbour City, 1 Canton Road, Tsimshatsui, Kowloon, Hong Kong
Tel: <852> 2265-6688, Fax: <852> 2730-6071

Renesas Technology Taiwan Co., Ltd.

10th Floor, No.99, Fushing North Road, Taipei, Taiwan
Tel: <886> (2) 2715-2888, Fax: <886> (2) 2713-2999

Renesas Technology (Shanghai) Co., Ltd.

Unit2607 Ruijing Building, No.205 Maoming Road (S), Shanghai 200020, China
Tel: <86> (21) 6472-1001, Fax: <86> (21) 6415-2952

Renesas Technology Singapore Pte. Ltd.

1 Harbour Front Avenue, #06-10, Keppel Bay Tower, Singapore 098632
Tel: <65> 6213-0200, Fax: <65> 6278-8001



Компания «ЭлектроПласт» предлагает заключение долгосрочных отношений при поставках импортных электронных компонентов на взаимовыгодных условиях!

Наши преимущества:

- Оперативные поставки широкого спектра электронных компонентов отечественного и импортного производства напрямую от производителей и с крупнейших мировых складов;
- Поставка более 17-ти миллионов наименований электронных компонентов;
- Поставка сложных, дефицитных, либо снятых с производства позиций;
- Оперативные сроки поставки под заказ (от 5 рабочих дней);
- Экспресс доставка в любую точку России;
- Техническая поддержка проекта, помощь в подборе аналогов, поставка прототипов;
- Система менеджмента качества сертифицирована по Международному стандарту ISO 9001;
- Лицензия ФСБ на осуществление работ с использованием сведений, составляющих государственную тайну;
- Поставка специализированных компонентов (Xilinx, Altera, Analog Devices, Intersil, Interpoint, Microsemi, Aeroflex, Peregrine, Syfer, Eurofarad, Texas Instrument, Miteq, Cobham, E2V, MA-COM, Hittite, Mini-Circuits, General Dynamics и др.);

Помимо этого, одним из направлений компании «ЭлектроПласт» является направление «Источники питания». Мы предлагаем Вам помощь Конструкторского отдела:

- Подбор оптимального решения, техническое обоснование при выборе компонента;
- Подбор аналогов;
- Консультации по применению компонента;
- Поставка образцов и прототипов;
- Техническая поддержка проекта;
- Защита от снятия компонента с производства.



Как с нами связаться

Телефон: 8 (812) 309 58 32 (многоканальный)

Факс: 8 (812) 320-02-42

Электронная почта: org@eplast1.ru

Адрес: 198099, г. Санкт-Петербург, ул. Калинина, дом 2, корпус 4, литера А.