

Power Limiter

SKU: 109990003



(images/product/Power Limiter_01.jpg)

Description

The RF Explorer Power Limiter is a custom device designed from scratch to be the perfect protection against strong RF fields.

As you can see on this note (<http://www.rf-explorer.com/care>) all RF Explorer models have some power ranges for input signal beyond which can be damaged. For most models, the limit is on +5dBm, some others are ok up to +10dBm but only WSUB3G (as well as the RF SMA connector on the right side in a 3G Combo) is protected up to +30dBm.

The new RF Explorer Power Limiter will allow any RF Explorer model to be protected with external signals up to +30dBm (1 Watt), so you get the same level of protection as in the WSUB3G. Furthermore, the power limiter includes additional functionality inside that will otherwise require external devices increasing cost and size:

- **Power limiter:** protection up to +30dBm, for any frequency range between DC-3000Mhz
- **DC block:** You can connect any external DC source up to 16V with no risk of damaging your RF Explorer or interfering in your measurement.
- **Attenuator:** Includes an internal 6dB attenuator to help you extend the range of power signal measurements. 6dB attenuation means only $\frac{1}{4}$ of the input power is received by the unit. To compensate for this extra attenuation you should indicate OffsetDB:+006 in the ATTENUATOR MENU of your RF Explorer.

The Power Limiter is assembled in a rugged aluminum case and it is very compact when compared to other market offerings, not to mention it includes internal DC block and attenuator which makes it a really small device for what it offers. It is a recommended add-on to all users who may expose their unit to strong external fields.

Feature

- Robust, small and low weight custom aluminum case
- 3-in-1 device with Power Limiter, DC Block and Attenuator
- Easy to connect and disconnect when required
- Wide broadband frequency application
- Directional 1 Watt rating
- Suitable for all RF Explorer models, not required for WSUB3G.

Specification

- Frequency range: DC ~ 3.0 GHz
- DC block: +16V DC
- Input Power rating: 1 Watt (+30dBm)
- Output power max: +4 dBm.

- Attenuation: 6 dB
- Impedance (Nominal): 50Ω
- V.S.W.R (Max): 1.25 : 1
- Connector type: SMA male – female
- Connector: Brass / Gold plating
- Body: Aluminum

If you encounter any problems when using this product, please contact [rfexplorer\(at\)arocholl.com](mailto:rfexplorer@arocholl.com) (<mailto:rfexplorer@arocholl.com>) for the technical support.

Overview



(<http://www.seeedstudio.com/depot/Maker-Pro-t-1672.html?ref=pinfo>)

Designer: RF Explorer

RF Explorer
Software Compatible

(<http://micro.arocholl.com/>)

Other Products From This Designer

(<http://www.seeedstudio.com/depot/RF-Explorer-m-22.html?ref=pinfo>)

Weight: 17 g



([/depot/OPLopen-parts-library-catalog-c-136_138/?ref=side](http://www.seeedstudio.com/depot/OPLopen-parts-library-catalog-c-136_138/?ref=side))



Компания «ЭлектроПласт» предлагает заключение долгосрочных отношений при поставках импортных электронных компонентов на взаимовыгодных условиях!

Наши преимущества:

- Оперативные поставки широкого спектра электронных компонентов отечественного и импортного производства напрямую от производителей и с крупнейших мировых складов;
- Поставка более 17-ти миллионов наименований электронных компонентов;
- Поставка сложных, дефицитных, либо снятых с производства позиций;
- Оперативные сроки поставки под заказ (от 5 рабочих дней);
- Экспресс доставка в любую точку России;
- Техническая поддержка проекта, помощь в подборе аналогов, поставка прототипов;
- Система менеджмента качества сертифицирована по Международному стандарту ISO 9001;
- Лицензия ФСБ на осуществление работ с использованием сведений, составляющих государственную тайну;
- Поставка специализированных компонентов (Xilinx, Altera, Analog Devices, Intersil, Interpoint, Microsemi, Aeroflex, Peregrine, Syfer, Eurofarad, Texas Instrument, Miteq, Cobham, E2V, MA-COM, Hittite, Mini-Circuits, General Dynamics и др.);

Помимо этого, одним из направлений компании «ЭлектроПласт» является направление «Источники питания». Мы предлагаем Вам помощь Конструкторского отдела:

- Подбор оптимального решения, техническое обоснование при выборе компонента;
- Подбор аналогов;
- Консультации по применению компонента;
- Поставка образцов и прототипов;
- Техническая поддержка проекта;
- Защита от снятия компонента с производства.



Как с нами связаться

Телефон: 8 (812) 309 58 32 (многоканальный)

Факс: 8 (812) 320-02-42

Электронная почта: org@eplast1.ru

Адрес: 198099, г. Санкт-Петербург, ул. Калинина, дом 2, корпус 4, литера А.