

1200W 120V Power Conditioner with Automatic Voltage Regulation (AVR) and AC Surge Protection

MODEL NUMBER: LC1200



Description

Tripp Lite's LC1200 Line Conditioner keeps your equipment working through brownouts and prolonged overvoltage conditions without using emergency power from UPS systems or auxiliary generators. Rated at 1200 watts / 10A, it automatically adjusts for under- and over-voltages to provide safe, computer-grade AC power meeting ANSI C84.1 specifications. It has a 7-ft AC power cord and 4 NEMA 5-15R outlets to provide continuous AC power to your critical IT equipment. With built-in premium surge suppression that exceeds the IEEE-587 standard for surge suppression (both categories A and B), the LC1200 also protects your valuable equipment from surges, spikes and EMI/RFI line noise that can wear down sensitive circuitry and cause premature aging or total failure of your equipment.

Features

- **Comprehensive Power Protection:** Provides comprehensive power protection for computers, A/V components and all electronics.
- **Automatic Voltage Regulation:** Built-in automatic voltage regulation (AVR) with three levels of voltage stabilization to provide a targeted response to overvoltages, undervoltages and severe brownouts. The LC1200 corrects brownouts as low as 89V and overvoltages up to 147V back to safe, nominal 120V power.
- **EMI/RFI Line Noise Filtering:** Electromagnetic and radio sources can cause disruptive interference on the AC line. This EMI/RFI line noise is a common cause of incremental hardware damage, data corruption and audio/video performance problems. The LC1200 incorporates technology that filters out disruptive line noise, preventing it from affecting your equipment or corrupting data.
- **Network Grade AC Line Surge Suppression:** The LC1200 provides 1200 joules of surge suppression to prevent even the strongest surges from damaging your valuable electronics. Includes full normal mode (H-N) and common mode (N-G/H-G) line surge suppression.
- **Built-In Power Status Display:** Seven diagnostic LEDs provide complete power status information: AC power (green = NORM), incoming voltage level (2 x yellow = HIGH/LOW, 2 x red = VERY HIGH/VERY LOW) and AC line status (green = LINE OK, red = LINE FAULT). An On/Off switch located on the rear of the unit provides one-touch power control over all components.
- **Compact Design:** The LC1200's compact cabinet (less than eight inches in height) and 7-ft. cord make it easy to integrate into a wide range of applications.
- **Ultimate Peace of Mind:** The LC1200 comes with \$25,000 Ultimate Lifetime Insurance—guaranteed lifetime protection for your equipment in case of

Highlights

- 1200 watt / 10 amp capacity
- Brownout and overvoltage protection in a single, cost-effective unit
- Maintains a regulated 120V nominal output over an input range of 89 to 147V
- Powerful 1200-joule surge suppression rating
- Four NEMA 5-15R outlets; 7 ft. AC power cord

Applications

- Maintains regulated output voltage during severe brownouts and overvoltages for computer accessories, printers, home theater equipment, a/v components, point-of-sale equipment, and other applications requiring clean, regulated AC power.

Package Includes

- LC1200 Line Conditioner
- Instruction manual



surge damage, including direct lightning strikes.

Specifications

OUTPUT	
Nominal Output Voltage(s) Supported	120V
Output Receptacles	(4) 5-15R
Output (VA)	1200
Output (Watts)	1200
INPUT	
Plug Type	Right-angle NEMA 5-15P input plug
Input Cord Length (ft.)	7
Input Cord Length (m)	1.83
USER INTERFACE, ALERTS & CONTROLS	
Front Panel LEDs	7 LEDs show incoming voltage status, protection present and line fault conditions
SURGE / NOISE SUPPRESSION	
UPS AC Suppression Joule Rating	1200 joules, conforms to IEEE 587 / ANSI C62.41 specifications
EMI / RFI AC Noise Suppression	75 dB
PHYSICAL	
Shipping Weight (lbs.)	8.7
Shipping Weight (kg)	4
Unit Dimensions (hwd / in.)	7.25 x 6 x 7
Unit Dimensions (hwd / cm)	18.4 x 15.2 x 17.8
Material of Construction	Plastic
Form Factors Supported	Small Tower
CERTIFICATIONS	
Certifications	Tested to UL1012 (USA), cUL1012 (Canada), NOM (Mexico)
WARRANTY	
Product Warranty Period (Worldwide)	2-year limited warranty



Tripp Lite
1111 W. 35th Street
Chicago, IL 60609 USA
Telephone: 773.869.1234
www.tripplite.com

Connected Equipment Insurance (U.S., Canada & Puerto Rico)	\$25,000 Ultimate Lifetime Insurance
---	--

© 2015 Tripp Lite. All rights reserved. All trademarks are the sole property of their respective owners. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice. Photos may differ slightly from final products.



Компания «ЭлектроПласт» предлагает заключение долгосрочных отношений при поставках импортных электронных компонентов на взаимовыгодных условиях!

Наши преимущества:

- Оперативные поставки широкого спектра электронных компонентов отечественного и импортного производства напрямую от производителей и с крупнейших мировых складов;
- Поставка более 17-ти миллионов наименований электронных компонентов;
- Поставка сложных, дефицитных, либо снятых с производства позиций;
- Оперативные сроки поставки под заказ (от 5 рабочих дней);
- Экспресс доставка в любую точку России;
- Техническая поддержка проекта, помощь в подборе аналогов, поставка прототипов;
- Система менеджмента качества сертифицирована по Международному стандарту ISO 9001;
- Лицензия ФСБ на осуществление работ с использованием сведений, составляющих государственную тайну;
- Поставка специализированных компонентов (Xilinx, Altera, Analog Devices, Intersil, Interpoint, Microsemi, Aeroflex, Peregrine, Syfer, Eurofarad, Texas Instrument, Miteq, Cobham, E2V, MA-COM, Hittite, Mini-Circuits, General Dynamics и др.);

Помимо этого, одним из направлений компании «ЭлектроПласт» является направление «Источники питания». Мы предлагаем Вам помощь Конструкторского отдела:

- Подбор оптимального решения, техническое обоснование при выборе компонента;
- Подбор аналогов;
- Консультации по применению компонента;
- Поставка образцов и прототипов;
- Техническая поддержка проекта;
- Защита от снятия компонента с производства.



Как с нами связаться

Телефон: 8 (812) 309 58 32 (многоканальный)

Факс: 8 (812) 320-02-42

Электронная почта: org@eplast1.ru

Адрес: 198099, г. Санкт-Петербург, ул. Калинина, дом 2, корпус 4, литера А.